

MC | 주식회사 미디어컨버전스

경기도 포천시 소흘읍 호국로 493-34 / (031) 876-4922(대표) / 1899-4922 (고객서비스센터) / www.mconver.co.kr


MC-4JL400



❖ Specification

- Light Source : 4pcs x 100W COB LED
- Color : RGBW and color mixing
- Brightness : R: 3,600LM, G: 5,000LM, B: 1,104LM, W: 5,200LM
- Strobe : 1~20 time/second, variable strobe effect
- DMX Channel : 8CH / 8CH
- Power Supply : AC100~240V, 50/60Hz
- Power Consumption : 400W
- Product Size : 350(W) x 370(H) x 200(D) mm
- Weight : 7Kg

[MENU SETTING]



Menu	Function	Value	Instruction		
R001	DMX address	001~512	UP, DOWN increase or reduce the value		
L001	DMX address	001~512	UP, DOWN increase or reduce the value		
d001	DMX address	001~512	UP, DOWN increase or reduce the value		
H000	Manual Mode	M000	Total dimming	M001	Dark
		M002	R bright	M003	G bright
		M004	R, G bright	M005	B bright
		M006	R, B bright	M007	G, B bright
		M008	R, G, B bright	M009	W bright
		M010	R, W bright	M011	G, W bright
		M012	R, G, W bright	M013	B, W bright

Menu	Function	Value	Instruction		
A000	Manual Mode	M014	R, B, W bright	M015	G, B, W bright
		M016	R,G,B,W bright	M017	Gradient
		M018	Pulse change	M019	RGBW circulate
		M020	WBGR circulate	M021	RG/BW circulate
		M022	RW/GB circulate	M023	RB/GW circulate
		M024	RG / GB / BW / WR circulate		
		M025	RGB / GBW / BWR circulate		
		M026	RGBW circulate	M027	Sound Active
S255	Strobe Speed	000~255	UP, DOWN change speed		
P255	Pulse Speed	000~255	UP, DOWN change speed		
r255	R Dimmer	000~255	UP, DOWN Change brightness		
G255	G Dimmer	000~255	UP, DOWN Change brightness		
b255	B Dimmer	000~255	UP, DOWN Change brightness		
W255	W Dimmer	000~255	UP, DOWN Change brightness		

DMX CHANNEL

[DMX Channel List / 8CH (A001)]

Channel	Value	Function	Channel	Value	Function
CH1	000~255	Total Dimming	CH2	000~255	Strobe
CH3	0~29	Total Dimming	CH3	30~34	Dark
	35~49	R bright		40~44	G bright
	45~49	R, G bright		50~54	B bright
	55~59	R, B bright		60~64	G, B bright
	65~69	R, G, B bright		70~74	W bright
	76~79	R, W bright		80~84	G, W bright
	85~89	R, G, W bright		90~94	B, W bright
	95~99	R, B, W bright		100~104	G, B, W bright
	105~109	R, G, B, W bright		110~139	Gradient
	140~169	Pulse change		170~179	RGBW circulate

Channel	Value	Function	Channel	Value	Function
CH3	180~189	WBGR circulate	CH3	190~199	RG/BW circulate
	200~209	RW/GB circulate		210~219	RB/GW circulate
	220~229	RG/WR circulate		230~239	RGB/GBW/BWR circulate
	240~249	RGBW circulate		250~255	Sound Active
CH4	000~255	Ch3 function speed	CH5	000~255	Red Dimming
CH6	000~255	Green Dimming	CH7	000~255	Blue Dimming
CH8	000~255	White Dimming			

[DMX Channel List / 4CH (L001)]

Channel	Value	Function	Remark
CH1	000~255	RGBW Dimmer	0~100%
CH2	000~255	Red, Blue Dimmer	0~100%
CH3	000~255	Green, White Dimmer	0~100%
CH4	000~255	Strobe Dimmer	0~100%

[DMX Channel List / 2CH (d001)]

Channel	Value	Function	Remark
CH1	000~255	Turned Light	
CH2	000~255	Brightness Dimmer	0~100%

제품보증규정

- 본 제품은 엄밀한 품질관리 및 검사과정을 거쳐서 만들어진 제품입니다.
- 제품이 제조상의 결함으로 인한 고장이 발생했을 경우에는 구입하신 날로부터 보증기간 중에는 무상으로 수리해 드립니다.
- 본 제품의 보증기간이 경과한 후에 발생한 고장에 대해서는 실비로 수리해 드립니다.

서비스 신고 안내

- 제품에 고장이 발생하였을 경우는 구입하신 대리점에 연락하시고, 처리 불가능시에는 고객 서비스 센터에 수리를 의뢰하여 주십시오.
- 신고하실 때에는 주소, 성명, 전화번호 및 집의 약도와 함께 고장상태, 불편한 사항을 알려주십시오.

미디어컨버전스 고객 서비스 안내

1899-4922