

MC | 주식회사 미디어컨버전스

경기도 포천시 소흘읍 호국로 493-34 / (031) 876-4922(대표) / 1899-4922 (고객서비스센터) / www.mconver.co.kr


MC-SL5150



❖ Specification

- Light Source : 5pcs x 30W LED (Red, Green, Blue), mixing(White)
- Color : RGB and color mixing
- Brightness : R: 690LM, G: 1,260LM, B: 360LM
- Strobe : 1~30 time/second, variable strobe effect
- DMX Channel : 3, 8, 15, 23CH (default setting : 8CH)
- Power Supply : AC100~240V, 50/60Hz
- Power Consumption : 150W
- Product Size : 570(W) x 110(H) x 140(D) mm
- Weight : 4.2 Kg

[MENU SETTING]



Menu	Function	Value	Instruction
R001	DMX address	001~512	UP, DOWN increase or reduce the value
08CH	DMX channel	/	UP, DOWN choose 03/08/15/23 channel
-512	Voice Control	/	Voice Control
E030	Effect Mode	001~030	UP, DOWN Choose mode
P255	Effect Speed	000~255	UP, DOWN Change speed
r255	R Dimmer	000~255	UP, DOWN Change brightness
G255	G Dimmer	000~255	UP, DOWN Change brightness
b255	B Dimmer	000~255	UP, DOWN Change brightness
F255	Strobe Speed	000~255	UP, DOWN Change speed

DMX CHANNEL

[DMX Channel List / 3CH]

Channel	Value	Function	Remark
CH1	000~255	Red Dimmer	0~100%
CH2	000~255	Green Dimmer	0~100%
CH3	000~255	Blue Dimmer	0~100%

[DMX Channel List / 8CH]

Channel	Value	Function	Remark
CH1	000~255	RGBW Dimmer	0~100%
CH2	000~255	Strobe	0~9 Dimming, 10~255 From Slow to Fast
CH3	000~255	Red Dimmer	0~100%
CH4	000~255	Green Dimmer	0~100%
CH5	000~255	Blue Dimmer	0~100%
CH6	001~255	Color Effect	1~24 R, 25~49 G, 50~74 B, 75~99 RG, 100~124 RB, 125~149 GB, 150~174 RGB, 175~199 Color Jump, 200~224 Color Statics, 225~255 Color Pulsation
CH7	000~255	Function Effect	0~9 blank, 10~16 R, 17~23 G, 24~30 B, 31~37 RG, 38~44 RB, 45~51 GB, 52~58 RGB, 59~65 Color Jump, 66~72 Color Statics, 73~79 Color Pulsation, 80~86 Effect_1, 87~93 Effect_2 94~100 Effect_3, 101~107 Effect_4 108~114 Effect_5, 115~121 Effect_6 122~128 Effect_7, 129~135 Effect_8 136~142 Effect_9, 143~149 Effect_10 150~156 Effect_11, 157~163 Effect_12 164~170 Effect_13, 171~177 Effect_14 178~184 Effect_15, 185~191 Effect_16 192~198 Effect_17, 199~205 Effect_18 206~212 Effect_19, 213~219 Effect_20 220~255 Voice Control
CH8	000~255	Function Speed	From Slow to Fast

DMX CHANNEL

[DMX Channel List / 15CH]

Channel	Value	Function	Remark
CH1	000~255	R1 Dimmer	0~100%
CH2	000~255	G1 Dimmer	0~100%
CH3	000~255	B1 Dimmer	0~100%
...
CH13	000~255	R5 Dimmer	0~100%
CH14	000~255	G5 Dimmer	0~100%
CH15	000~255	B5 Dimmer	0~100%

[DMX Channel List / 23CH]

Channel	Value	Function	Remark
CH1	000~255	RGBW Dimmer	0~100%
CH2	000~255	Strobe	0~9 Dimming, 10~255 From Slow to Fast
CH3	000~255	Red Dimmer	0~100%
CH4	000~255	Green Dimmer	0~100%
CH5	000~255	Blue Dimmer	0~100%
CH6	001~255	Color Effect	1~24 R, 25~49 G, 50~74 B, 75~99 RG, 100~124 RB, 125~149 GB, 150~174 RGB, 175~199 Color Jump, 200~224 Color Statics, 225~255 Color Pulsation
CH7	000~255	Function Effect	0~9 blank, 10~16 R, 17~23 G, 24~30 B, 31~37 RG, 38~44 RB, 45~51 GB, 52~58 RGB, 59~65 Color Jump, 66~72 Color Statics, 73~79 Color Pulsation, 80~86 Effect_11, 87~93 Effect_12 94~100 Effect_13, 101~107 Effect_14 108~114 Effect_15, 115~121 Effect_16 122~128 Effect_17, 129~135 Effect_18 136~142 Effect_19, 143~149 Effect_20 150~156 Effect_21, 157~163 Effect_22 164~170 Effect_23, 171~177 Effect_24 178~184 Effect_25, 185~191 Effect_26 192~198 Effect_27, 199~205 Effect_28 206~212 Effect_29, 213~219 Effect_30 220~255 Voice Control

DMX CHANNEL

CH8	000~255	Function Speed	From Slow to Fast
CH9	000~255	R1 Dimmer	0~100%
CH10	000~255	G1 Dimmer	0~100%
CH11	000~255	B1 Dimmer	0~100%
...
CH21	000~255	R5 Dimmer	0~100%
CH22	000~255	G5 Dimmer	0~100%
CH23	000~255	B5 Dimmer	0~100%

제품보증규정

- 본 제품은 엄밀한 품질관리 및 검사과정을 거쳐서 만들어진 제품입니다.
- 제품이 제조상의 결함으로 인한 고장이 발생했을 경우에는 구입하신 날로부터 보증기간 중에는 무상으로 수리해 드립니다.
- 본 제품의 보증기간이 경과한 후에 발생한 고장에 대해서는 실비로 수리해 드립니다.

서비스 신고 안내

- 제품에 고장이 발생하였을 경우는 구입하신 대리점에 연락하시고, 처리 불가능시에는 고객 서비스 센터에 수리를 의뢰하여 주십시오.
- 신고하실 때에는 주소, 성명, 전화번호 및 집의 약도와 함께 고장상태, 불편한 사항을 알려주십시오.

미디어컨버전스 고객 서비스 안내

1899-4922