


## MC-2JL200



### ❖ Specification

- Light Source : 200 LEDs ( Red, Green, Blue, White )
- Color : RGBW and color mixing
- Brightness : R: 1,800LM, G: 2,640LM, B: 540LM, W: 3,000LM
- Strobe : 1~20 time/second, variable strobe effect
- DMX Channel : 8CH / 8CH
- Power Supply : AC100~240V, 50/60Hz
- Power Consumption : 200W
- Product Size : 340(W) x 150(H) x 150(D) mm
- Weight : 2.7 Kg

### [ MENU SETTING ]



Menu	Function	Value	Instruction
A001	DMX address	001~512	UP, DOWN increase or reduce the value
d001	DMX address	001~512	UP, DOWN increase or reduce the value
FF99	Color Fade	01~99	UP, DOWN Change speed
EE99	Color Pulse	01~99	UP, DOWN Change speed
CC99	Color Jump	01~99	UP, DOWN Change speed
Sound	Sound Active	/	Sound Active
r255	R Dimmer	000~255	UP, DOWN Change brightness
G255	G Dimmer	000~255	UP, DOWN Change brightness
b255	B Dimmer	000~255	UP, DOWN Change brightness
W255	W Dimmer	000~255	UP, DOWN Change brightness

## DMX CHANNEL

## [ DMX Channel List / 8CH (A001) ]

Channel	Value	Function	Remark
CH1	000~255	RGBW Dimmer	0~100%
CH2	000~255	Strobe	0~9 blank, 10~255 Slow - Fast
CH3	000~255	Effect program	
CH4	000~255	Speed for CH3	
CH5	000~255	Red Dimmer	0~100%
CH6	000~255	Green Dimmer	0~100%
CH7	000~255	Blue Dimmer	0~100%
CH8	000~255	White Dimmer	0~100%

## [ DMX Channel List / 8CH (d001) ]

Channel	Value	Function	Remark
CH1	000~255	RGBW Dimmer	0~100%
CH2	000~255	Red Dimmer	0~100%
CH3	000~255	Green Dimmer	0~100%
CH4	000~255	Blue Dimmer	0~100%
CH5	000~255	White Dimmer	0~100%
CH6	000~255	Strobe	0~9 blank, 10~255 Slow - Fast
CH7	000~255	Effect program	
CH8	000~255	Speed for CH7	

## 제품보증규정

- 본 제품은 엄밀한 품질관리 및 검사과정을 거쳐서 만들어진 제품입니다.
- 제품이 제조상의 결함으로 인한 고장이 발생했을 경우에는 구입하신 날로부터 보증기간 중에는 무상으로 수리해 드립니다.
- 본 제품의 보증기간이 경과한 후에 발생한 고장에 대해서는 실비로 수리해 드립니다.

## 서비스 신고 안내

- 제품에 고장이 발생하였을 경우는 구입하신 대리점에 연락하시고, 처리 불가능시에는 고객 서비스 센터에 수리를 의뢰하여 주십시오.
- 신고하실 때에는 주소, 성명, 전화번호 및 집의 약도와 함께 고장상태, 불편한 사항을 알려주십시오.

## 미디어컨버전스 고객 서비스 안내

1899-4922