


MC-EL200



❖ Specification

- Light Source : 200 LEDs (Red, Green, Blue, White)
- Color : RGBW and color mixing
- Brightness : R: 1,200LM, G: 2,100LM, B: 600LM, W: 3,300LM
- Strobe : 1~20 time/second, variable strobe effect
- DMX Channel : 4CH / 8CH
- Power Supply : AC100~240V, 50/60Hz
- Power Consumption : 200W
- Product Size : 180(W) x 180(H) x 600(D) mm
- Weight : 8.1 Kg

[MENU SETTING]



- Address — 001-512 — 512 Address Setting
- Mode
 - DMX_CH4 — Console 4CH
 - DMX_CH8 — Console 8CH
 - Auto 1 — Jump Speed: 0-99
 - Auto 2 — Gradient Speed: 0-99
 - Auto 3 — Pulse Speed: 0-99
 - Auto 4 — Jump, Gradient, Pulse Mix
 - Sound — Empty
- Adjust
 - RED — RED Dimming
 - Green — Green Dimming
 - Blue — Blue Dimming
 - White — White Dimming
 - Curve — Dimming Mode, 5pcs Dimming Mode
 - Temp — Lamp Temp Display

DMX CHANNEL

[DMX Channel List / 4CH]

Channel	Value	Function	Remark
CH1	000~255	Red Dimmer	0~100%
CH2	000~255	Green Dimmer	0~100%
CH3	000~255	Blue Dimmer	0~100%
CH4	000~255	White Dimmer	0~100%

[DMX Channel List / 8CH]

Channel	Value	Function	Remark
CH1	000~255	Red Dimmer	0~100%
CH2	000~255	Green Dimmer	0~100%
CH3	000~255	Blue Dimmer	0~100%
CH4	000~255	White Dimmer	0~100%
CH5	000~255	RGBW Dimmer	0~100%
CH6	000~255	Strobe	0~9 blank, 10~255 Slow - Fast
CH7	000~255	Self-Propelled	0~9 blank, 10~200 Self-Propelled
CH8	000~255	Self-Propelled Speed	From Slow to Fast

제품보증규정

- 본 제품은 엄밀한 품질관리 및 검사과정을 거쳐서 만들어진 제품입니다.
- 제품이 제조상의 결함으로 인한 고장이 발생했을 경우에는 구입하신 날로부터 보증기간 중에는 무상으로 수리해 드립니다.
- 본 제품의 보증기간이 경과한 후에 발생한 고장에 대해서는 실비로 수리해 드립니다.

서비스 신고 안내

- 제품에 고장이 발생하였을 경우는 구입하신 대리점에 연락하시고, 처리 불가능시에는 고객 서비스 센터에 수리를 의뢰하여 주십시오.
- 신고하실 때에는 주소, 성명, 전화번호 및 집의 약도와 함께 고장상태, 불편한 사항을 알려주십시오.

미디어컨버전스 고객 서비스 안내

1899-4922